

*A1* --The invention pertains to a displacement sensor with a meander-shaped measuring winding.--

Page 1, after line 12 insert the following heading centered on the page:

*Ar* --SUMMARY OF THE INVENTION--

Page 3, after line 17 insert the following heading centered on the page:

*A3* --BRIEF DESCRIPTION OF THE DRAWINGS--

Page 3, replace the paragraph beginning on line 18, with the following rewritten paragraph:

--Additional advantages and features of the invention can be derived from the following description and from the drawings in which:

*A4* Figure 1a shows a schematic diagram of an embodiment of a sensor according to the invention;

Figure 1b is an end view of Figure 1a;

Figure 2 shows a schematic diagram of the voltage which can be tapped from the sensor illustrated in Figure 1a and of the magnetic induction;

Figure 3 shows a schematic diagram of the induction occurring in the sensor shown in Figure 1a;

Figure 4a shows a different embodiment of an inductive sensor making use of the invention;

Figure 4b is a section view taken on the line A-B in Figure 4a;

Figure 5a shows a schematic diagram of an exemplary embodiment of a sensor;

and

Figures 5b and 5c shown the induction course in directions x and y, respectively.--

Page 4, after line 3 insert the following heading centered on the page:

**--DESCRIPTION OF THE PRESENTLY PREFERRED EMBODIMENTS--**

Page 4, replace the paragraph beginning on line 4 with the following rewritten paragraph:

-- Figure 5a shows an arrangement consisting of a core 31 with an air gap, in which a printed-circuit board 30 is present. A coil, through which current passes, generates an alternating field in the core, which permeates the printed-circuit board 30. The broken lines represent lines of equal induction. The diagrams (Figures 5b and 5c) next to and below these lines show the course of the induction in the direction of motion of the measuring head (x direction) and crosswise to that (the y direction). The physical circumstances make it impossible to arrive at a perfectly linear course. In contrast, it is possible to achieve a curve with good symmetry in the x direction but not in the y direction. To avoid sensitivity to lateral displacements (y direction), the induction loop is designed so that it consists of conducting tracks 32 which extend in the direction of motion of the measuring core and also perpendicular

*Ab cond.* to the direction of motion; they thus form rectangles, which project deeply into the air gap of the measuring core and thus absorb practically all of the magnetic flux in this area.--

\ Page 4, replace the paragraph beginning on line 19 with the following rewritten paragraph:

*AS* --Figures 1a and 1b show a design of this type. On the printed-circuit board 1 is a meander-shaped conducting track 2, one end of which is connected to an electrical connecting terminal 4 by the conducting track 3, whereas the other end is connected to connecting terminal 5. The measuring core 6 has a winding 7, through which an alternating current flows. The production of this alternating current is not described in detail here. It can be derived from, for example, DE 197-57,689.3-52 and from PCT/DE98/03,753, to which reference is made here.--

*AS* \ Page 8, replace the paragraph beginning on line 17, with the following rewritten paragraph:

*AS* --Figures 4a and 4b show a schematic diagram of an angle sensor for measuring angles over a range of  $360^\circ$  and a section view through the sensor. On a rotatably supported shaft 17, a measuring core 16 is mounted by a holder 16a in such a way that a stationary, ring-shaped printed-circuit board 15, which is concentric to the shaft, lies in the air gap of the measuring core 16. When the shaft rotates, the measuring core 16 passes over the conducting tracks 18, 19. The two conducting tracks 18, 19 are applied to opposite sides of the printed-circuit board 15. Both have the same geometry but are offset  $90^\circ$  from each other. The conducting track 18 is shown on the top. It is divided into two halves, and in the middle it is connected by a

Ag  
cond.

—

19